

THUNDERBIRD

BX108

Technical Specifications

Version 1.1 September 2002

ENGLISH



BEHRINGER

INSTRUMENT AMPLIFICATION

SPECIFICATIONS

AUDIO INPUTS

Guitar input	1/4" mono jack, approx. 200 k Ω unbalanced
Tape input	Cinch connector, approx. 68 k Ω unbalanced

AUDIO OUTPUTS

Phones output	1/4" stereo jack
Tape output	Cinch connector, approx. 1 k Ω unbalanced

SYSTEM SPECIFICATIONS

Power amp output	15 Watts / 8 Ω
------------------	-----------------------

LOUDSPEAKER

Type	8" special custom-made speaker
Impedance	8 Ω
Power handling	25 Watts

POWER SUPPLY

Mains voltages	U.S./Canada	120 V \sim , 60 Hz
	U.K./Australia	240 V \sim , 50 Hz
	Europe	230 V \sim , 50 Hz
	General export model	100 - 120 V \sim , 200 - 240 V \sim , 50 - 60 Hz
Power consumption	max. 25 Watts	
Fuse	100 - 120 V \sim : T 500 mA H	
	200 - 240 V \sim : T 250 mA H	
	Standard IEC receptacle	
Mains connection	Standard IEC receptacle	

PHYSICAL

Dimensions (H x W x D)	approx. 369 mm (14.5") x 330 mm (13") x 229 mm (9.1")
Weight	approx. 7 kg

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may differ from those listed or illustrated.

The information contained in this manual is subject to change without notice. No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of BEHRINGER Spezielle Studioteknik GmbH.

BEHRINGER and THUNDERBIRD are registered trademarks.

ALL RIGHTS RESERVED. © 2002 BEHRINGER Spezielle Studioteknik GmbH.
BEHRINGER Spezielle Studioteknik GmbH, Hanns-Martin-Schleyer-Str. 36-38, 47877 Willich-Münchheide II, Germany
Tel. +49 (0) 21 54 / 92 06-0, Fax +49 (0) 21 54 / 92 06-30
