

Genelec 1030A Bi-amplified Monitoring System

Data sheet



1030A Bi-amplified Active Monitoring System



SYSTEM

The Genelec 1030A is a very compact bi-amplified active monitor system, which has performance comparable to much larger systems. The vented speaker enclosure has an amplifier unit set into the back. This unit contains an active electronic crossover, overload protection circuitry and two power amplifiers: one for each driver. The system's excellent dispersion and precise imaging together with its compact size make it ideal for near field monitoring, broadcast and TV control rooms. mobile vans, home studios and travelling engineers.

Genelec's unique Directivity Control Waveguide (DCW) technology is used to provide excellent stereo imaging and frequency balance, even in difficult acoustic environments and the versatile crossover controls allow further matching of the system to its surroundings. A pair of 1030As can produce peak acoustic levels of over 115 dB SPL at 1m. The speakers may be used in vertical or horizontal orientation.

INTEGRATED CONSTRUCTION

Because the amplifiers are built into the speaker enclosure, the only connections required are the mains supply and the line level input signal, making the 1030A very easy to set up and use. The integrated design allows the amplifiers and the drivers to be calibrated as a single unit, thus eliminating the effects of component tolerances and ensuring consistent quality. The MDF cabinet has rounded corners and a hard-wearing painted outer surface and this simple, rugged construction and the pivoting antivibration amplifier mounting make maintenance very easy and straightforward.



Block diagram, showing active crossover filters, power amplifiers and driver units.

AMPLIFIERS

The bass and treble amplifiers produce 80 W and 50 W of short term power respectively, with very low THD and IM distortion values, and are designed to ensure the highest subjective sound quality currently possible. The amplifier unit also contains circuitry that detects levels above the drivers' safe limits and prevents any damage, making the system immune to overloads and spurious signals which digital equipment and synthesizers often produce.



Horizontal mounting







The two channel amplifier is housed in the speaker cabinet

Near Field Monitoring Broadcast Monitoring Surround Sound Monitoring TV Control Rooms Mobile Vans Video Post Production

APPLICATIONS

Project / Home Studios

Digital Workstations



The reference axis lies between bass and treble drivers.

DRIVERS

A 19 mm (3/4") metal dome driver, loaded by a proprietary DCW, is used to reproduce the high freauencies.

The bass driver is a high efficiency 170 mm (6¹/2") polymer composite cone driver in a 6.5 liter vented cabinet. The -3 dB frequency is 52 Hz and the low frequency response extends down to 47 Hz. (-6dB)

Both drivers are magnetically shielded for applications such as video post production, where stray magnetic fields must be minimized.

console output.

CROSSOVER FILTERS

The amplifier unit contains an ac-

tive crossover, a feature more

commonly used in large and expensive control room monitors. This

is the ideal method for dividing the

input signal between the driver units, and allows the overall re-

sponse of the system to be

optimized to an extent impossible with a passive system.

To maintain uniform frequency bal-

ance in differing acoustic environments, three special calibrated controls are included in the active crossover network: treble and bass 'tilt' and bass 'roll-off' switches, which make adjust-

ments in 2 dB steps. The system

input is a balanced XLR, with ad-

justable sensitivity, to allow easy signal matching with the mixing

> switch. MUTE disconnects the channel for testing.

Calibrated 'Tilt'



The upper curve group shows the horizontal directivity characteristics of 1030A measured at 1 m. The lower curve is the 1/2 octave band power response.





The treble driver is mounted in a DCW to match its dispersion characteristics to those of the bass driver. The DCW may be rotated for horizontal or vertical mountina.

DCWTECHNOLOGY

The revolutionary Directivity Control Waveguide (DCW) technology is a means of greatly improving the performance of a direct radiating multi-way loudspeaker under normal listening conditions. One of the basic aims is to match the performance of the drivers in terms of both frequency response and directivity. This results in a smoother overall frequency response on and off axis. In addition, the improved directivity control causes more direct sound and less reflected sound to be received at the listening position. This provides improved stereo imaging and ensures the system is less sensitive to differing control room acoustics than any conventional direct radiator design. The DCWTechnology improves the drive unit sensitivity by +2 to +6 dB (depending on the particular application), thus increasing the available system maximum sound pressure level

The curves show the effect of the 'bass tilt', 'treble tilt' and 'bass rolloff' controls on the free field response.

Options





Opt-04 Wall Mount Order Code 1030-404-V 1030-404-H

0pt-09

Order Code

1030-409

Grille



Opt-05 Floor stand Order Code 1030-405-V 1030-405-H



GENELEC®

1030A SYSTEM SPECIFICATIONS

Lower cut-off frequency, -3 dB: \leq 52 Hz						
Upper cut-off frequency, -3 dB: \geq 20 kHz						
Free field frequent		cyresponse 55 Hz - 18 kHz (± 2.5 dB)				
Maximum short term sine wave acoustic output on axis in half space, averaged from 100 Hz to 3 kHz:						
100 T IZ 10 3 KI IZ.		@ 1m @ 0.5m	≥ 105 dB SPL ≥ 111 dB SPL			
Maximum long term RMS acoustic output in same conditions with IEC weighted noise (limited by driver unit protection circuit): @ 1m \geq 99 dB SPL @ 0.5m \geq 105 dB SPL						
Maximum peak acoustic output per pair on top of console, @ 1 m from the engineer with music material: $\geq 115 \text{ dB}$						
Self generated noise level in free field @ 1m on axis: \leq 10 dBA						
Harmonic	distorti	on at 90 dB SPL @ 1m on				
axis:	Freq:	60150 Hz < 3% > 150 Hz < 0.5%				
Drivers:	Bass Treble Both dr shielde	170 mm 19 mm ivers are d.	$(6 \frac{1}{2})$ cone $(3/_{4})$ metal dome magnetically			
Weight:		7,6 kg	(17 lb)			
Dimensions:		Height Width Depth	312 mm (12 ¹ / ₄ ") 200 mm (7 ⁷ / ₈ ") 240 mm (9 ¹ / ₂ ")			

AMPLIFIER SECTION

Bass amplifier output power with an 4 Ohm load:

80 W

Treble amplifier output power with an 8 Ohm load:

50 W

Long term output power is limited by driver unit protection circuitry.

Amplifier system	n distortion at	
nominal output:		
	THD	<u><</u> 0.08%
	SMPTE-IM	<u><</u> 0.08%
	CCIF-IM	<u><</u> 0.08%
	DIM 100	<u><</u> 0.08%

Signal to Noise ratio, referred to full output:

	Bass Treble	≥ 95 dB ≥ 95 dB	
Mains voltage:	100/200 or 115/230 V		
Voltage operating 230V setting: 115V setting:	range at 207 - 253 V (± 10%) 104 - 126 V (± 10%)		
Power consumption	on: Idle Full output	20 VA 100 VA	

CROSSOVER SECTION

Input connector: XLR female pin 1 gnd pin 2 +

, pin 3 -

Input impedance: 10 kOhm balanced

Input level for 100 dB SPL output @ 1m: variable from +6 to -6 dBu

Input level for maximum short term sine wave output of 105 dB SPL @ 1m: variable from +11 to -1 dBu

Subsonic filter below 50 Hz : 18 dB/octave

Ultrasonic filter above 25 kHz: 12 dB/octave

Crossoverfrequency, Bass/Treble: 3.5 kHz

Crossover acoustical slopes: 24 - 32 dB/octave

Treble tilt control operating range in 2 dB steps: from +2 to -4 dB & MUTE

Bass roll-off control operating range in 2 dB steps: from 0 to -8 dB @ 50 Hz

Bass tilt control operating range in 2 dB steps: from 0 to -6 dB @ 100 Hz & MUTE

The 'CAL' position is with all tone controls set to 'off' and the input sensitivity control to maximum (fully clockwise).

GENELEC®

Genelec Oy, Olvitie 5 FIN - 74100 IISALMI, FINLAND Phone: +358 - 17 - 813311 Telefax: +358 - 17 - 812267 E-mail: genelec@genelec.com Web: http://www.genelec.com

Genelec Inc, 7 Tech Circle Natick, MA 01760, USA Phone: +1 - 508/652-0900 Fax: +1 - 508/652-0909 Email: genelec@compuserve.com



Genelec Document BBA30001 COPYRIGHT GENELEC OY 4/1999 All data subject to change without prior notice