



ROLLS

VP29 Phono Preamp

- Converts RIAA Phono signals to Line Level
- Works well with magnetic phono pickups
- Stereo RCA and 1/8" outputs

Phono players require special equalization because of the frequency response of recording on vinyl. The VP29 equalizes and amplifies the phono signal to a clean, and full line level for professional amplification.

What's in the box?

- 1 - Made in USA VP29
- 1 - 15V power supply PN PS27s
- 1 - This owners manual

VP29 PHONO PREAMP

SPECIFICATIONS

I/ O Connectors:	RCA, 1/8" TRS Stereo
Input Sensitivity:	42 dB gain 1kHz, 47k Ohms
Input Capacitance:	120pf
Sensitivity:	5mV for 635mV output
Input Impedance:	50k Ohms
Output Impedance:	1K Ohms
Frequency Response:	+ / - .5 dB 20 Hz - 20 kHz (Conforms to RIAA Equalization Curve)
THD	.01% @ 1 kHz
S/N Ratio:	>83 dB unweighted
PWR:	9 - 15 VDC
Size:	3.25 x 2 x 1.5
Weight:	1 lb